

# QUEST 2 LED IOT

## GENERAL CARD



## TECHNICAL PARAMETERS

|                               |                    |
|-------------------------------|--------------------|
| Ingress protection:           | IP65; IP66         |
| Impact resistance:            | IK09               |
| Nominal power [W]:            | 103.00; 108.00     |
| Luminous flux [lm]*:          | 13500; 14700       |
| Colour temperature [K]:       | 3000; 5000         |
| Color rendering index (Ra) >: | 80                 |
| SDCM:                         | 3                  |
| Electrical protection class:  | I                  |
| Energy efficiency class:      | C; D               |
| Material of the body:         | aluminium          |
| Colour of the body:           | anthracite grey    |
| Diffuser material:            | glass              |
| Diffuser type:                | transparent        |
| Beam angle [°]:               | 120; ASW           |
| Mounting version:             | surface            |
| Working temperature [°C]:     | from -20 to +35    |
| Dimensions (H/W/T/S) [mm]:    | 321/424/37;        |
| PZH certificate:              | B-BK-60212-0480/21 |

## CHARACTERISTICS

High-quality floodlight with inbuilt LED source. The body is made of die-cast aluminium, powder coated in anthracite grey (RAL 7016), and the mounting bracket is made of black-painted steel. The diffuser is made of 5 mm thick tempered glass. It is equipped with directional lens matrices with 3 different light distributions: symmetrical (120°), asymmetric narrow ASN and asymmetric wide ASW. Non-corrosive mounting bracket allowing for adjustment angles between -140° to +185°. The luminaire is available in 2 sizes: M and L. Standard equipped with 0.1m long H07RN-F cable and IP66 quick connector. Wide range of accessories available: protective net, grip for the lighting pole, wall bracket.

### IoT characteristics

Variants available:

**IoT RC PIR HYT DALI** has **PIR** motion and light sensor programmed by **RC** remote control and **DALI** driver enabling dimming of the light source.

**IoT BT PIR HYT DALI Bluetooth HYT** module controlled in the Lena Lighting Clue application, **PIR** motion and light sensor, **DALI** driver enabling dimming of the light source.

**IoT RC PIR HYT PIR** motion and light sensor programmed by **RC** remote control and ON/OFF driver without light source dimming function.

## APPLICATION

Lighting of educational, educational and administrative facilities, halls, garages, passages, warehouses, shops, food industry and commercial and service facilities related to food products.

# QUEST 2 LED IOT

GENERAL CARD

## AVAILABLE VERSIONS




Click index >>, to see details

| Nominal power [W] | Colour temperature [K] | Luminous flux [lm]* | Beam angle [°] | Ingress protection | PIR | DIMM DALI | Version         | Index                           |
|-------------------|------------------------|---------------------|----------------|--------------------|-----|-----------|-----------------|---------------------------------|
| 108               | 5000                   | 14700               | 120            | IP66               | yes | yes       | RC PIR HYT DALI | <a href="#">&gt;&gt; 695025</a> |
| 103               | 3000                   | 13500               | ASW            | IP65               | yes | yes       | RC PIR HYT DALI | <a href="#">&gt;&gt; 699658</a> |


# QUEST 2 LED IOT

## GENERAL CARD

### LUMINOUS INTENSITY DISTRIB. CURVE



QUEST 2 LED ASW rozsył  
asymetryczny szeroki



QUEST 2 LED rozsył symetryczny 120°

Card creation date: 22 October 2025

The company reserves the right to make design changes or upgrades in the presented product. Product data sheet does not constitute an offer. \* Parameter tolerance is +/- 10%



This product is a subject to electric and electronic waste equipment regulations (WEEE).



Certificate CE - Nr: 86/2021



Lena Lighting S.A.  
ul. Kórnicka 52, 63-000 Środa Wielkopolska  
tel. +48 61 28 60 333 (Pn-Pt, 8-16), e-mail: hello@lenalighting.pl, www.lenalighting.pl

---

## Quest 2 LED IoT - explanation of the different versions:

The **IoT RC PIR HYT DALI** version has: **PIR** motion and daylight sensor programmable by the **RC** remote control and **DALI** driver enabling dimming of the light source.

The **IoT BT PIR HYT DALI** version has: a built-in **BT HYT** module that allows you to program functions in the Lena Lighting Clue app and control in real time; **PIR** motion and daylight sensor and **DALI** driver for dimming the light source.

The **IoT RC PIR HYT** version has: **PIR** motion and daylight sensor programmable by **RC** remote control and **ON/OFF** driver without dimming function of the light source.