

# SPARK EYE LED

DETAILED CARD



## TECHNICAL PARAMETERS

<b>Index:</b>	607646
<b>Ingress protection:</b>	IP44
<b>Luminous flux of the luminaire [lm] - range:</b>	160 - 640
<b>Supply voltage [V]:</b>	3.7
<b>Electrical protection class:</b>	III
<b>Color rendering index (Ra) &gt;:</b>	80
<b>Charging time [h:min]:</b>	3
<b>Battery life [h:min]:</b>	2.5-10
<b>Battery:</b>	Li-Ion 3,7V
<b>Dimensions (H/W/T/S) [mm]:</b>	250/87/50

## CHARACTERISTICS

This work light is the perfect solution for mechanics, tradespeople and DIY enthusiasts. It is a modern work light that allows you to direct the beam in various directions (thanks to its swivel head). The lamp is designed to illuminate the work area. It is particularly useful in garages servicing cars, vans and lorries. The replaceable battery can be charged separately (away from the lamp) using a C-type connector.

## APPLICATION

Car repair shops (repairs for cars, vans and lorries), car detailing centres, car washes, mobile repair services, etc.

# SPARK EYE LED

DETAILED CARD

## TECHNICAL PARAMETERS TABLE

<b>Index:</b>	607646	<b>Diffuser type:</b>	transparent
<b>EAN:</b>	5905963607646	<b>Colour of the body:</b>	black
<b>Light source:</b>	LED	<b>Dimensions (H/W/T/S) [mm]:</b>	250/87/50
<b>Luminous flux of the luminaire [lm] - range:</b>	160 - 640	<b>Ingress protection:</b>	IP44
<b>Supply voltage [V]:</b>	3.7	<b>Working temperature [°C]:</b>	from -20 to +35
<b>Electrical protection class:</b>	III	<b>Switch:</b>	yes
<b>Color rendering index (Ra) &gt;:</b>	80	<b>Magnet:</b>	yes
<b>Charging time [h:min]:</b>	3	<b>Net weight [kg]:</b>	0.310
<b>Battery life [h:min]:</b>	2.5-10	<b>Accessories included:</b>	1 x 2600mAh 3.7V Li-Ion battery with a Type-C charging port – the battery can be charged separately from the lamp
<b>Light colour:</b>	biały	<b>CE certificate:</b>	<a href="#">62/2026</a>
<b>Battery:</b>	Li-Ion 3,7V	<b>Manual:</b>	<a href="#">Download PDF</a>
<b>Battery capacity [mAh]:</b>	2600		

# SPARK EYE LED

DETAILED CARD

## ACCESSORIES AVAILABLE

index	Name
607660	External charger for Li-ion batteries: 3.7V / 2600 mAh (SPARK LED lamp range)
607677	Replaceable Li-ion battery: 3.7V / 2600 mAh (SPARK LED lamp range)

Card creation date: 08 May 2026

The company reserves the right to make design changes or upgrades in the presented product. Product data sheet does not constitute an offer. \* Parameter tolerance is +/- 10%



This product is a subject to electric and electronic waste equipment regulations (WEEE).



Certificate CE - Nr: 62/2026



Lena Lighting S.A.  
ul. Kórnicka 52, 63-000 Środa Wielkopolska  
tel. +48 61 28 60 333 (Pn-Pt, 8-16), e-mail: hello@lenalighting.pl, www.lenalighting.pl